

sKyact.Panic LoRa

LoRaWAN Push Button

LoRaWAN® smart button for wireless control, alarms, and triggers. sKyact.Panic supports multiple user-defined press actions to control devices or activate scenes. Compact and battery-powered, the device is easy to install and to carry everywhere.

Features

- Support multiple press actions
- Easily to install or carry with the convenient size
- Built-in LED indicator and buzzer for press actions, network status, low battery indication
- Ultra-wide-distance wireless transmission: 15 km in line of sight scene



IoT Sensors

Product Features	
Product Code	50.100003.007
Technology	LoRaWAN®
Frequency	CN470/IN865/RU864/EU868/US915/AU915/KR920/AS923
Tx Power	16 dBm (868 MHz)/22 dBm (915 MHz)/19 dBm (470 MHz)
Sensitivity	-137 dBm @300bps
Infrared Area	11+8+6+5 (typical)
Button	1 × External Button + 1 ×
LED Indicator	1
Buzzer	Support
Power Supply	1 × 1650 mAh ER14335 Li-SOCI2 battery
Battery Life*	6.5 years (10 presses per day)
Operating Temperature	-30°C to +60°C
Ingress Protection	IP30
Dimension	50 × 50 × 18 mm (1.97 × 1.97 × 0.71 in) Button: Φ20 mm (Φ0.79 in)
Material	Anti-flaming Polycarbonate
Installation	On the flat surfaces with screws or 3M tapes, Lanyard
Warranty	1 year